


## DS90-PR 3" Designer Series Passive Radiator



## **FEATURES**

- Perfect match for Dayton Audio's paper cone Designer Series drivers
- Allows tuning small enclosures lower than using conventional ports
- Rear mounted screw allows easy mass adjustment for custom tuning
- Cosmetic frame edge looks great even when surface mounted

PARAMETERS	
Fs	42.4 Hz
Qms	5.9
Mms	5.5g
Cms	2.55 mm/N
Sd	31.2 cm <sup>2</sup>
Vd	12.5 cm <sup>3</sup>
Vas	3.5 liters
Xmax	4 mm
Rms	0.3 kg/s

 $\textbf{Note:} \ \mathsf{Parameters} \ \mathsf{above} \ \mathsf{are} \ \mathsf{for} \ \mathsf{the} \ \mathsf{passive} \ \mathsf{only} \ \mathsf{with} \ \mathsf{no} \ \mathsf{additional} \ \mathsf{mass} \ \mathsf{added}.$